

Energy Saving

High Sensitivity Detector

- Utilizes the infrared energy from human as control signal source
- Adopts good sensitivity detector, integrated circuit , SMD
- Wide Detection Field
- Starts load at once when one enters detection field
- Identify day and night automatically
- Sensitivity adjustable according to using location: Low sensitivity for small room/ high sensitivity to fit large room
- Easy to install and use



Detection Range : 360°
Detection Distance : 6m Max. (<24°C)
Power source : 220-240V/AC
Power Frequency : 50Hz
Ambient Light : 10Lux/2000Lux (choice)
Time Delay : 5sec./30sec./1min./3min./5min./8min.
Rated Load : 800W (Incandescent lamp)
 200W (energy-saving lamp)
Working Tempt. : -20°C ~ +40°C
Working Humidity : 93%RH
Installation Height : 1.8 ~ 2.5m
Power consumption : 0.45W(work)
 0.1W (static)
Detection Motion Speed : 0.6 ~ 1.5m/s

VandalVeto®