

Energy Saving

Infrared Motion Sensor

- Utilizes the infrared energy from human as control signal source
- Adopts good sensitivity detector, integrated circuit
- Starts load at once when one enters detection field
- Identify day and night automatically
- Easy to install and use

Detection Range : 180°
Detection Distance : 12m Max. (24°C)
Power source : 220-240V/AC
Power Frequency : 50/60Hz
Ambient Light : 3-2000Lux (adjustable)
Time Delay : 10sec. +/- 3sec. (min)
7min. +/- 2min. (max)
Rated Load : 1200W/220V (Incandescent lamp)
300W/220V (energy-saving lamp)
Working Temp. : -20°C ~ +40°C
Working Humidity : 93%RH
Installation Height : 1.8 ~ 2.5m
Power consumption : 0.34W (work)
0.1W (static)



VandalVeto®